Connect 42 Media Full-HD+ 100 DR+ Welcome to the age of networked entertainment.

- Loewe LCD-TV with 106 cm screen diagonal and high definition Full-HD-100Hz-technology.
- Receive Internet radio, with over 8.000 stations worldwide.
- Direct access to all multimedia content on the home network. PhotoViewer and MusicBox via USB







## **Technical information**

### Image:

- Automatic Movie Detection (AMD)
- Brightness cd/m2: 500
- Contrast adjustment depending on ambient light (OCP)
- Contrast ratio dynamic/static: 11.000 : 1/1.400 : 1
- Contrast sensor
- Downscaling/upscaling
- Format options: 16:9,4:3, Panorama, Cinema, Zoom
- Full-HD LCD technology
- Fully digitised signal processing
- HD ready
- HDTV-ready
- Horizontal and vertical viewing angle: 178°/178°
- Image resolution: 1.920 x 1.080
- Image+ Active
- Motion picture display 24 p
- PIP (AV)/Full PIP/iPIP
- Picture format/screen diagonal in cm: 16:9/106
- Picture frequency 100 Hz
- Response time: 5 ms
- Split Screen TV/TV, TV/Videotext [1]
- Vertical image correction

- Audio Out, controlled
- Audio output power in Watts: 2 x 20
- Closed 2-way speakers
- Number of speakers: 4 PRX sound system
- Subwoofer Out
- Tone effects: Stereo, Panorama, 3D Surround
- Two-channel stereo sound

- Automatic station identification
- EPG [2]
- Radio function: with DVB-C/DVB-S [3]

### Operation:

- Assist+
- Automatic Channel Programming (ACP)
- Automatic Signal Switch (ASS) Automatic Volume Control (AVC) [4]
- Automatic shut-off
- Channel identification
- Channel-specific volume adaptation
- Content-sensitive help

- Current TV Programme [2]
- DR+ / storage capacity 250 GB
- Digital Link, Digital Link Plus, Digital Link HD
- Electronic Instruction Manual
- Electronic Program Guide (EPG): (analogue/digital) [2]
- Index
- I-Link
- Media network for accessing multimedia content in the network  $% \left( 1\right) =\left( 1\right) \left( 1\right$
- NexTView-Link [2]
- On Screen Display (OSD) in foreign languages: D-E-I-F-NL-GB-P-PL-CZ-DK-S-HU-FIN-SLN-TR-SK-RS-GR
- Parental Lock
- Personalised teletext with direct access to bookmarked
- PhotoViewer
- Power switch
- Programme positions (incl. AV and radio): 4.000
- Remote control: Assist 2
- Teletext: TOP-/FLOF-Teletext/Level 2.5
- Teletext page memory: 2.000
- Video Time
- via control unit: 5 keys

### Reception:

- Audio standard: FM Two-channel/AM, Nicam
- Colour standard: PAL, SECAM, NTSC, NTSC-V, PAL-V (60 Hz)
- Decoding System Audio: MPEG
- Decoding System Video: MPEG 2/MPEG 4
- Television standard: B/G, D/K, I, L, M, N
- Tuner: DVB-T, DVB-C; analogue: cable, antenna

### Connectors:

- Antenna (analogue/digital): 2
- Audio In (Cinch)
- Audio Out, controlled (Cinch)
- Common Interface: 1
- Component (YUV) input
- Copy function Euro-AV <-> Euro-AV
- Copy function Front-AV --> Euro-AV
- Digital-Audio In/Out (Cinch)
- Ethernet port RI45
- Euro-AV/Scart total: 2
- Euro-AV/Scart, of which the following number are Component Video Input-ready: 1

- Euro-AV/Scart, of which the following number are RGB-ready: 1
- Euro-AV/Scart, of which the following number are S-VHS/Hi8-ready: 2
- HDMI including HDCP: 3
- Headphones: 3,5 mm
- S-Video In
- Side AV Video-/S-VHS, Hi-8 ready
- USB: 2
- VGA
- Video In (cinch)
- Wireless-LAN antennae

### Optional function upgrades:

- DVB-S 2 (Single-Tuner) [5]
- DVB-S 2 (Twin-Tuner) [5] Dolby Digital / dts [6]
- Motor control/ RS 232 C / IR-Link

- Equipment board for Floor Stand Trapeze
- Set-up solutions: Floor Stand Trapeze (can be adjusted to three heights); manual rotation; Floor Stand 4; motorised rotation: Floor Stand 4 MU, Floor Stand 5 MU SP
- Standard feature: Table Stand (manual rotation incl.)
- VESA adapter: VESA C 42
- Wall Mount: WM 54, Screen Wall Mount 52 L [7]

### Miscellaneous:

- Mains voltage: 220 240 V / 50/60 Hz
- Power consumption in standby mode in watts: 0,9
- Power consumption in watts when the set is turned off: 0  $\,$
- Rated wattage to EN 62087 (2009): 170
- VDE-safety standard (inspection seal)
- Weight (net) in kg: 27,2

# Technical specifications, delivery conditions, and other information are subject to change without notice.

- [1] Not with MPEG4.
- Works only with channels broadcasting service information/NexTView data
- DVB-S only with integrated DVB-S 2 (Tuner) Function depends on signal format emitted by station.
- Not available for MHEG5 models.
- $\ensuremath{\mathsf{Dolby}}$  is a registered trademark of the  $\ensuremath{\mathsf{Dolby}}$  Laboratories Licensing Corporation. Only in conjunction with a corresponding adapter, to be ordered



